

## STATIC BREAKER BACKUP RELAY TYPE SBC99AG

## INTRODUCTION

This supplement together with GEK-45464 constitutes the instructions for the SBC99AG special relay.

## DESCRIPTION

The SBC99AG relay is the same as the SBC23B except it has the following ratings:

| DC Control Voltage<br>Frequency | 250 VDC<br>50 Hz   |
|---------------------------------|--|
| Continuous Current              | 2.0 Amps   |
| Phase Current Pickup Levels     | 0.2-0.4 Amp<br>0.4-0.8 Amp<br>0.8-2.0 Amps These ratings not |
| Residual Current Pickup Levels  | 0.1-0.2 Amp<br>0.2-0.4 Amp<br>0.4-1.0 Amp                    |

The AC burden for each of the transformer circuits is given in Table I.

TABLE I
Burden for One Amp, 50 Hz Relays\*

| Transactor | Tap Setting (Amps) | Impedance (Ohms) | Power Factor (Deg-Lag) |
|------------|--------------------|------------------|------------------------|
| Phase      | 0.2-0.4            | 0.286            | 27.0                   |
| н          | 0.4-0.8            | 0.116            | 16.3                   |
| ŧı         | 0.8-2.0            | 0.052            | 9.0                    |
| Residual   | 0.1-0.2            | 0.838            | 38.0                   |
| 11         | 0.2-0.4            | 0.286            | 27.0                   |
| ii .       | 0.4-1.0            | 0.116            | 16.3                   |

<sup>\*</sup>These relays are rated two amps continuous (at the specified frequency) when set on the maximum phase tap setting.

These instructions do not purport to cover all details or variations in equipment nor to provide for every possible contingency to be met in connection with installation, operation or maintenance. Should further information be desired or should particular problems arise which are not covered sufficiently for the purchaser's purposes, the matter should be referred to the General Electric Company.

To the extent required the products described herein meet applicable ANSI, IEEE and NEMA standards; but no such assurance is given with respect to local codes and ordinances because they vary greatly.